



RC-8000

Master Remote Control Panel



The **RC-8000** is a master remote control unit for the Kramer series 88 matrix switchers (VS-88A, VS-88V, SD-7588A and the VS-7588V). It can control up to 8 switchers and an unlimited number of control panels.

FEATURES

- Input/Outputs Interface - RS-485.
- Memory Locations - Stores multiple switches as presets to be recalled and executed when needed.
- ALL / OFF Controls - Sends one input to all outputs, can disconnect all outputs, or turn off individual outputs.
- Audio Breakaway Switching.
- Control - 8 switchers via front panel pushbuttons.



RC-8000

TECHNICAL SPECIFICATIONS

INPUT/OUTPUT: 1 x RS - 485 connector on a detachable terminal block.

CONTROL: 8 illuminated pushbuttons each assigned to a different controlled unit address. 8 out/8 in/5 operational pushbuttons similar to the "88" matrix switcher series.

POWER SOURCE: 12 V DC, 200 mA.

SOURCE:

DIMENSIONS: 21.6 cm x 3.8 cm x 14 cm (8.5" x 1.5" x 5.5", W, D, H.).

WEIGHT: 0.4 kg (0.9 lbs.) approx.

ACCESSORIES: Power supply, mounting bracket.