



## VS-41AV

4x1 Composite Video & Stereo Audio Mechanical Switcher

---



The **VS-41AV** is a high-performance switcher for composite video and unbalanced stereo audio signals. It switches any one of four inputs to a single output.

### FEATURES

---

- High Bandwidth - 520MHz (-3dB).
- Mechanical (Passive) Switching - No power required.
- Desktop Size - Compact size. 2 units can be rack mounted side-by-side in a 1U rack space with the optional RK-81 adapter.



## VS-41AV

### TECHNICAL SPECIFICATIONS

**INPUTS:** 4 video, 1Vpp/75Ω on BNC connectors. 4 audio stereo, +4dBu typical, on RCA connectors.

**OUTPUTS:** 1 video, 1Vpp/75Ω on a BNC connector. 1 audio stereo, +4dBu typical, on RCA connectors.

**SWITCHING SYSTEM:** Mechanical, break-before-make, audio-follow-video mode.

**BANDWIDTH (-3dB):** 520MHz (video), 100kHz (audio).

**CROSSPOINTS:** 4 for video, 4x2 for audio, 1 set active at any given time.

**SIGNAL LEVELS:** Up to 3Vpp video, +30dBu audio.

**DIMENSIONS:** 18.8cm x 10.2cm x 4.4cm (7.4" x 4" x 1.7") H, W, D.

**WEIGHT:** 0.65kg (1.44lbs) approx.

**OPTIONS:** RK-81 19" rack adapter.

